



# X1000 Pro

## d.light X1000 Pro

The revolutionary d.light X1000 Pro Solar home system grows with your aspirations, powering multiple appliances, accessories, mobile phones, and bright light after just a single day of charge. Each unit comes bundled with a bright tube light, 3 LED lamps and 1 security lamp.

# Solar Home System



# TECHNICAL INFORMATION



## Rechargeable battery

100 hours of light per full charge



## Charger

Charges mobiles via USB port



## PayGo

Pay in easy installments

<b>Solar panel</b>	40W, 18V, 2.22Ah, Polycrystalline
<b>Battery</b>	128Wh LiFePo4 Battery (10Ah at 12.8V)
<b>Battery life span</b>	Up to 8 years of daily use (2000+ cycles)
<b>Max lumen-hour (VeraSol)</b>	10,000
<b>Lights</b>	5 lights (1 tube + 3 bulbs+1security) with wall mount switches
<b>LED lifespan</b>	60,000 hours+
<b>Maximum runtime</b>	10 hours at high settings, 100 hours at low settings
<b>Mobile charging</b>	3 USB ports (5V at 1A)
<b>Wireless connectivity</b>	Yes (Auto token transfer)
<b>DC output port</b>	3 12V DC output ports
<b>PayGo enabled</b>	d.light Atlas, Solaris PaygOps, Angaza Energy Hub, Paygee, Upya
<b>Ingress protection</b>	Dust & splash proof, IP20 (Solar panel IP44)
<b>d.light warranty</b>	2 year limited warranty
<b>Certifications</b>	VeraSol certified tested to IEC TS 62257-9-5 and certified to the quality standards in IEC TS 62257-9-8. MSDS (for battery only)
<b>Minimum order quantity</b>	500pcs
<b>Units in a master carton</b>	4 units
<b>Units quantities in a 20' GP</b>	1,368 units
<b>Units quantities in a 40' HQ</b>	3,136 units

## In the box

(1) Control Box, (3) Bulb Lights, (1) Tube Light, (1)Security light,(1) 40W Solar Panel (separately), Wall Screws, Binding Wire, Cable Clips Instruction Manual.



# VeraSol

